

SPECIFICATIONS

RF Isolation:

> 50 dBmV @ 750 MHz

Sense Input:

+ 15 dBmV maximum

Drop-Out Level:

- 3 dBmV; Delay 250 mSec

Pick-Up Level:

0 dBmV; Delay 25 mSec

**Power Requirement for
External Power Supply:**

100-240 VAC \pm 2%, 50/60 Hz.

Physical:

1.50" H x 2.75" W x 5.25" D

Weight:

1 lb.

Emergency Messaging Platforms CATV switching and Control

100 Housel Ave., P.O. Box 535
Lyndonville, NY 14098
(585)765-2254 (585)765-1155
fax (585)765-9330

www.digitalalertsistemas.com

Copyright © 2010-2019 Digital Alert Systems Inc.
Information herein is considered accurate at the time of
publication. We constantly strive to improve our products
and services therefore some specifications are subject to
change without notice. One-Net^{SE}, DASDEC-II, MultiStation,
Multiplayer, EAS-Net, EAS-CAP, CMPro and CMPlus are
trademarks of Digital Alert Systems Inc. Other logos and
trademarks are property of their respective owners.
All rights reserved.

RF/IF Sensor Model 625A

FEATURES

- Small size
- 'F' connectors
- Unused signals terminated in 75 Ω
- Includes 12 VDC power pack
- Flanged enclosure for easy mounting
- External Solid State Switch, driven by Sensor



DESCRIPTION

The Model 625A RF/IF Sensor provides automatic 2x1 RF/IF switching controlled by the loss of video modulated RF carrier.

The 625A's sense input circuit monitors horizontal sync pulses on the video modulated RF carrier and automatically switches to the secondary input upon a decrease or loss. The relay remains in this state with the secondary input connected to the output, until the sync pulses on the video modulated RF carrier return. This causes the primary input to switch back to the output connection.

The 625A's sensing input requires an external bandpass filter and pad for multiple channel feed conditions.