


Model 627A Stereo A/V Switch Instruction Sheet



Installation

1. Connect your main audio/video common outputs to your equipment's inputs.
2. Connect the power supply wires, White to +12 V and Black to Ground, to the terminal block connections marked.
3. Dry contact across ground and CNTRL will change the output from the primary to the secondary when closed

***Relay connection:** Connect the normally open (NO) contact to **Ctrl**. Connect the relay common (COM) contact to **GND**.

Operation

The 627A's primary inputs are normally connected to the common outputs. It remains in this state until the **Ctrl** input is connected to **Gnd**. This will connect the secondary input to common for the duration of the connection.

Specifications

Video/RF

75Ω ; 'F' connectors

Audio

Balanced stereo; screw terminals

Video/RF Isolation @ 950 MHz

> 52 dB

Video-IF/RF Return Loss

> 22 dB

Control Input

<2 mA maximum to GND

Power Requirement

100-240 VAC ±2%, 50/60 Hz.
Power pack output; +12 VDC

Physical

5.25"H x 2.75"W x 2"D
Weight 1 lb

WARRANTY

Digital Alert Systems, Inc. warrants to the owners, each instrument and sub-assembly manufactured by them to be free from defects in material and workmanship for a period of two years after shipment from factory. This warranty is applicable to the original purchaser only.

Liability under this warranty is limited to service, adjustment or replacement of defective parts (other than fuses and batteries) on any instrument or sub-assembly returned to the factory for this purpose, transportation charges prepaid.

This warranty does not apply to instruments or sub-assemblies subjected to abuse, abnormal operating conditions, or unauthorized repair or modification.

Since Digital Alert Systems, Inc. has no control over conditions of use, no warranty is made, or implied as to the suitability of our product for the customer's intended use.

THE WARRANTY SET FORTH IN THIS ARTICLE IS EXCLUSIVE AND IN LIEU OF ALL OTHER WARRANTIES AND REPRESENTATIONS, EXPRESS, IMPLIED OR STATUTORY INCLUDING, BUT NOT LIMITED TO THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS. Except for obligations expressly undertaken by Digital Alert Systems, in this warranty, Owner hereby waives and releases all rights, claims and remedies with respect to any and all warranties, express, implied or statutory (including without limitation, the implied warranties of merchantability and fitness), and including but without being limited to any obligation of Digital Alert Systems with respect to incidental or consequential damages, or damages for loss of use. No agreement or understanding varying or extending the warranty will be binding upon Digital Alert Systems unless in writing signed by a duly authorized representative of Digital Alert Systems.

In the event of a breach of the foregoing warranty, the liability of Digital Alert Systems shall be limited to repairing or replacing the non-conforming goods and/or defective work, and in accordance with the foregoing, Digital Alert Systems shall not be liable for any other damages, either direct or consequential.

RETURN POLICY TO FACTORY

Materials returned to Digital Alert Systems must have a Return Material Authorization number. To obtain a RMA number, contact our A/V Switching & Control Customer Service at 585-765-2254 or fax 585-765-9330. Customers have 30 days to determine that the product ordered fills their need and performs as described in the applicable literature. Units returned for approved repair or credit, must be in the original packaging including all parts and paperwork plus be in very good physical condition. If not, the customer is billed the cost to refurbish the unit and for missing accessories and merchandise. No products may be returned for exchange or credit after 12 months of the shipment date. Digital Alert Systems reserves the right to repair or replace units under warranty.