

SPECIFICATIONS

Isolation:

> 42 dBmV @ 950 MHz

Frequency Response:

± 2 dBmV 0 to 950 MHz

Control Input:

1 mA maximum to ground

Stereo Audio:

DPDT w/screw terminals

**Power Requirement for
External Power Supply:**

100-240 VAC ± 2%, 50/60 Hz

Physical:

1.75" H X 19" W X 7" D

Weight:

2 lbs.

Stereo A/V or IF/RF Switch

Model R164

FEATURES

- Video Switch works from 0 to 750 MHz
- BNC connectors
- Unused signals terminated in 75 Ω
- Includes power pack
- Standard 19 inch rack



DESCRIPTION

Model R164 Stereo Audio/Video Switch module provides 2x1 (AB) balanced stereo audio follow video or IF/RF switching.

The 2x1 switch will respond to a contact closure, a transistor switch to ground or a compatible logic level. The control input is buffered to eliminate high output current drive requirements of the controlling device.

The R-164 can be controlled by program timers, remote controls or CATV Cue Tone receivers.

Emergency Messaging Platforms CATV switching and Control

100 Housel Ave., P.O. Box 535
Lyndonville, NY 14098
(585)765-2254 (585)765-1155
fax (585)765-9330

www.digitalalertsystems.com

Copyright © 2010-2019 Digital Alert Systems Inc.
Information herein is considered accurate at the time of publication. We constantly strive to improve our products and services therefore some specifications are subject to change without notice. One-Net^{SE}, DASDEC-II, MultiStation, Multiplayer, EAS-Net, EAS-CAP, CMPPro and CMPPlus are trademarks of Digital Alert Systems Inc. Other logos and trademarks are property of their respective owners.
All rights reserved.