

Specifications

Number of Cue Tone Sequences:

1 set of On/Off standard,
2 to 4 optional

Output Impedance:

600 Ω , balanced

Cue Tone Output Level:

Adjustable, 2 mV to 2 V RMS

Cue Tone Delay Time:

Adjustable, 0.25 to 1.75 Sec.

Cue Tone Transmission Rate:

Adjustable, 5 to 200 digits/Sec.

Power Requirements:

94 - 240 VAC, ± 10 %, 50/60 Hz UL/
CSA/CE supply

Physical:

3.5" H x 9.5" D x 19" W
Weight: 4 lbs.

Emergency Messaging Platforms CATV switching and Control

100 HouseI Ave., P.O. Box 535
Lyndonville, NY 14098
(585)765-1155 fax (585)765-9330

www.digitalalertsystems.com

Copyright © 2010-2018 Digital Alert Systems
Information herein is considered accurate at the time of
publication. We constantly strive to improve our products
and services therefore some specifications are subject to
change without notice. DASDEC, MultiStation, and EAS-Net
are trademarks of Digital Alert Systems Inc. Other logos and
trademarks are property of their respective owners.
All rights reserved

Applications

- **Programming Changes**
- **East Coast - West Coast Programming**
- **Return From Blackout Programming**
- **Switch to Local Origination Programming**
- **Beginning and Ending of Daily Programming**
- **Beginning and Ending of Scrambled Programming**
- **Beginning and Ending of Local Commercial Avails**



Description

The Model R-103A Cue Tone Encoder is the preferred method of sending control signals over program audio or audio grade links.

Front panel pushbutton switches or external contact closures, initiate the DTMF® Cue Tone sequence. Included relays allow the Cue Tones to be placed on interrupted program audio if desired, or on a separate voice grade audio sub-carrier.

Indicator lights on the front panel verify that the tones generated are the proper sequence.

Remote indicators may be switched from screw terminals on the rear panel.