

SPECIFICATIONS

Video:

> 70 dBmV @ 100 MHz

IF/RF:

> 52 dBmV @ 950 MHz

Stereo Audio:

Balanced, detachable screw terminals

Clock Accuracy:

±1 sec per day @ 20° C

Power Requirement for External Power Supply:

100-240 VAC + 2 %, 50/60 Hz

Physical:

2.0" H X 4.25" W X 6.5" D 5.25" D

Weight:

1 lb.

Emergency Messaging Platforms CATV switching and Control

100 House Ave., P.O. Box 535
Lyndonville, NY 14098
(585)765-2254 (585)765-1155
fax (585)765-9330

www.digitalalertsystems.com

Copyright © 2010-2019 Digital Alert Systems Inc. Information herein is considered accurate at the time of publication. We constantly strive to improve our products and services therefore some specifications are subject to change without notice. One-Net^{SE}, DASDEC-II, MultiStation, Multiplayer, EAS-Net, EAS-CAP, CMPro and CMPlus are trademarks of Digital Alert Systems Inc. Other logos and trademarks are property of their respective owners. All rights reserved.

Program Timer Jr. Model 631A

FEATURES

- **Small size**
- **'F' connectors**
- **Unused Video terminated to 75 Ω**
- **Balanced stereo audio**
- **Six ON/OFF commands per day**
- **Block programming for Monday through Friday**
- **Battery backup of clock on power loss (1 AA)**
- **Includes power pack**
- **May be used for IF/RF from 0 to > 950 MHz.**



DESCRIPTION

The Program Timer Jr. provides a 2x1 (AB) balanced stereo audio follow video switch, with separate timed commands.

The 631A has been designed to be as simple as possible to program. Setting the time of day, programming of individual days, or an entire weekly schedule is accomplished with only five keystrokes. Manual override of output is accomplished with a single key stroke.

Four selectable block program variations allow for quick and simple programming:

Monday through Friday
Monday through Saturday
Monday through Sunday
Saturday/Sunday